

METHOD AND APPARATUS FOR AVOIDING CACHE POLLUTION DUE TO
SPECULATIVE MEMORY LOAD OPERATIONS IN A MICROPROCESSOR

5

BACKGROUND OF THE INVENTION

Field of the Invention

The present invention relates generally to the
10 storage of data in a microprocessor cache memory, and
more particularly to a system, method, and
microprocessor architecture for avoiding cache pollution
caused by speculative memory operations.

15 Description of Related Art

Early computer processors, also called
microprocessors, included a central processing unit or
instruction execution unit that executed only one
instruction at a time. Early microprocessors also
20 executed instructions in an order determined by the
compiled machine-language program running on the
microprocessor and so are referred to as "sequential"
microprocessors. In response to the need for improved
performance, several techniques have been used to extend
25 the capabilities of these early microprocessors
including pipelining, superpipelining, superscaling, and
speculative instruction execution.

Pipelined architectures break the execution of instructions into a number of stages where each stage corresponds to one step in the execution of the instruction. Pipelined designs increase the rate at which instructions can be executed by allowing a new instruction to begin execution before a previous instruction is finished executing. Pipelined architectures have been extended to "superpipelined" or "extended pipeline" architectures where each execution pipeline is broken down into even smaller stages (i.e., microinstruction granularity is increased).

Superpipelining increases the number of instructions that can be executed in the pipeline at any given time.

"Superscalar" microprocessors generally refer to a class of microprocessor architectures that include multiple pipelines that process instructions in parallel. Superscalar microprocessors typically execute more than one instruction per clock cycle, on average. Superscalar microprocessors allow parallel instruction execution in two or more instruction execution pipelines. The number of instructions that may be processed is increased due to parallel execution.

The goal of superscalar and superpipeline microprocessors is to execute multiple instructions per microprocessor clock cycle. Instruction-level

parallelism, such as Single Instruction Multiple Data instructions, available in programs can be exploited to realize this goal. Full exploitation of this potential parallelism requires that instructions be dispatched for
5 execution at a sufficient rate.

However, the ability of modern high performance microprocessors to execute instructions has typically outpaced the ability of memory subsystems to supply instructions and data to the microprocessors. Thus,
10 most high-performance modern microprocessors use cache memory systems with at least one level of high speed, on-chip cache memory to speed memory access.

Cache memory, sometimes simply called "cache", comprises one or more levels of dedicated high-speed
15 memory for holding recently accessed instructions and data, designed to speed up subsequent access to the same instructions or data. Cache technology is based on the premise that programs frequently re-execute the same instructions or execute different instructions on
20 recently accessed data.

When data is read from main memory, a cache system saves a copy of the data in the cache memory, along with an index to the associated main memory. The cache system then monitors subsequent requests for data to see
25 if the information needed has already been stored in the

cache.

If the cache system indicates that the data had indeed been stored in the cache, sometimes called a cache "hit", the data is delivered immediately to the microprocessor and the attempt to fetch the information from main memory is aborted (or not started). If, on the other hand, the data had not been previously stored in cache, sometimes called a cache "miss", then the requested data is fetched directly from main memory and also saved in the cache for future access.

Each cache entry is typically accessed by a unique address "tag" stored separately in a tag random access memory (RAM). A cache "hit" occurs whenever a memory access to the cache occurs and the cache system finds, through inspecting its tag memory, that the requested data is present and valid in the cache.

In superscalar microprocessors, multiple pipelines could simultaneously process instructions only when there were no data dependencies between the instructions in each pipeline. For example, when an instruction that operates on data fetched from memory is dependent upon one or more preceding instructions to load the required data into working operand registers, the dependent instruction cannot execute until all of the required stored data has been retrieved from cache or main

memory.

Microprocessor instruction execution units in an execution pipeline cannot predict how long it may take to load data into the working operand registers
5 specified by a particular load operation.
Microprocessors typically handled this uncertainty by delaying execution until the fetched data is returned by "stalling" the execution pipeline. Consequently data dependencies caused one or more pipelines to wait for
10 the dependent data to become available. This stalling was inconsistent with high speed, multiple instruction per cycle processing.

Speculative instruction execution was an attempt to address pipeline "stalls" in deeply pipelined
15 microprocessors caused by data load operation uncertainty. Modern microprocessors pipeline memory operations allowed a second load operation to enter a load/store stage in an execution pipeline before a previous load instruction, the results on which the
20 second load operation depends, has passed completely through the execution pipeline.

In such deeply pipelined, speculative instruction execution microprocessors, a dependent load instruction, sometimes called a consumer load instruction, dependent
25 on a sequentially earlier load instruction, sometimes

called a producer load instruction, may be scheduled for issue before confirmation that the load data required by the consumer load instruction is available in cache memory.

5 In such microprocessors there is a delay between the decision to issue an instruction and the actual execution of the instruction. Thus, in the case of load instructions, there may exist a significant delay between the issue of a load instruction and data fetch
10 from cache memory. The load instruction is often said to be "in-flight" during this delay. Accordingly, a consumer load instruction, dependent on an "in-flight" producer load instruction, may be issued before the confirmation by the cache system that the load data
15 required by the consumer load instruction is available in the cache. When the required data is not found in the cache, such dependent consumer load instructions could be executing with incorrect data operands. Consumer load instructions, directly or indirectly
20 dependent on "in-flight" producer load instructions, executing with incorrect data operands, send erroneous data to the main memory and cache memory. Such consumer load instructions may cause useful data to be replaced in cache with erroneous data, i.e., data that will
25 likely not be referenced by sequentially later program

instructions. This replacement of erroneous data with
useful data in the cache, sometimes referred to as cache
pollution, often leads to poor cache system performance
and thereby adversely effects processor performance and
5 system throughput.

What is needed is a method and apparatus for
minimizing or eliminating cache pollution caused by
speculative memory load operations.

10 SUMMARY OF THE INVENTION

Embodiments of the present invention provide a
method and microprocessor architecture to eliminate
cache pollution caused by speculative memory load
operations. The method includes determining whether a
15 data dependency between particular consumer load
instructions and a particular, sequentially earlier,
producer load instructions is "true" or "false". The
various dependency states of the consumer load
instructions on the producer load instructions,
20 sometimes called dependency state intersections, are
then written to and stored in a cache pollution
avoidance unit.

As used herein, a "true" dependency state condition
of a given consumer load instruction on a given producer
25 load instruction exists whenever the consumer load

instruction depends on the results returned by the
producer load instruction to provide operand data to the
consumer load instruction. A "false" dependency state
condition exists whenever the consumer load instruction
5 does not depend on the producer load instruction to
provide operand data.

Further, a "true" dependency state is said to be
"direct" whenever no other instructions, upon which the
consumer load instruction also depends, sequentially
10 intervene between the producer load instruction and the
consumer load instruction. If any other instructions,
upon which the consumer load instruction also depends,
do sequentially intervene between the producer load
instruction and the consumer load instruction, the
15 dependency of the consumer load instruction on the
producer load instruction is said to be "indirect".

As may be appreciated, in one embodiment, a
particular load instruction may be both a producer load
instruction for a sequentially later load instruction
20 which depends on the particular load instruction, while
at the same time may be a consumer load instruction of a
sequentially earlier load instruction from which the
particular load instruction depends.

After the cache pollution avoidance unit acquires
25 the "true"/"false" dependency state condition of a

dependency state intersection between a consumer load instruction and a producer load instruction, the cache pollution avoidance unit acquires from the cache system the "miss" state in cache for operand data supplied at
5 the completion of the producer load instruction and required by the dependent consumer load instruction.

In one embodiment of the invention, the cache "miss" state condition for operand data required by the consumer load instruction is next logically ANDed with
10 the dependency state condition of the consumer load instruction on the producer load instruction.

The cache pollution avoidance unit of the present invention suppresses execution of, sometimes called squashing or being squashed, the consumer load
15 instruction, thereby disallowing memory access to the consumer load instruction, whenever the logically ANDing of the dependency state condition and the cache "miss" state condition indicates both a "true" dependency condition for the consumer load instruction on the
20 producer load instruction and a cache "miss" for the required consumer load instruction operand data.

Whenever an "in-flight" consumer load instruction is squashed by the cache pollution avoidance unit, the consumer load instruction is prevented from accessing
25 main memory. Since, the consumer load instruction does

not access main memory, erroneous data is not fetched into cache memory. Accordingly, use of the method of the present invention, employing a cache pollution avoidance unit, eliminates cache pollution caused by
5 speculative memory operations of load instructions in a microprocessor.

In one embodiment, the various dependency state conditions between consumer load instructions and producer load instructions are stored as one-bit binary
10 condition "flags" in a conventional RAM array making up a dynamic memory dependency table within the cache pollution avoidance unit. A "true" dependency state condition is represented by a binary bit value of "1" stored in a RAM memory cell and a "false" dependency
15 state condition is represented by a bit value of "0".

Further in this embodiment, a "true" cache "miss" is represented by a "1" bit value returned by the cache system of the microprocessor to the cache pollution avoidance unit. A "false" cache "miss", i.e., a cache
20 "hit", is represented by a bit value of "0" returned by the cache system of the microprocessor to the pollution avoidance unit.

Still further in this embodiment, the logical ANDing of the dependency state condition and the cache

"miss" state condition is "true" when the logical ANDing outputs a bit value of "1".

Thus, in one embodiment of the invention, the logical ANDing of the dependency state condition and the cache "miss" state condition outputs a "1" bit value, whenever both the dependency state of a consumer load instruction on a producer load instruction, stored in the dynamic memory dependency table, has a bit value of "1", and the cache pollution avoidance unit returns a bit value of "1", i.e., a cache "miss" for operand data produced by the producer load instruction and required by the consumer load instruction. In this embodiment, if the output of the logical ANDing by the cache pollution avoidance unit has a bit value of "1", memory access is squashed for the dependent consumer load instruction.

In one embodiment, after each determination of a "true" ANDing condition, the consumer load instruction is rescheduled by the microprocessor instruction scheduling unit and the logical ANDing of the dependency state and the cache "miss" state is re-determined by the cache pollution avoidance unit.

Once the logical ANDing of the dependency state condition of the consumer load instruction on the producer load instruction and the cache "miss" state

condition is "false", i.e. when the cache "hits", the squash memory access for the dependent consumer load instruction is released by the cache pollution avoidance unit.

5 In this embodiment, the logical ANDing is "false" whenever the producer instruction has completed execution, the results of the producer instruction stored in registers, and the results copied to the cache. In this embodiment, the dependency between the
10 producer load instruction and the consumer load instruction is de-asserted, i.e., set to logical "0". After this point, the logical ANDing between the dependency state and the cache "miss" state is "false" since the registers contain the operand data required by
15 the dependent consumer load instruction. The consumer load instruction is then able to compute the correct address and access memory and related cache to load the properly referenced load data.

 In one embodiment of the invention, the logical
20 ANDing of the dependency state and the cache "miss" state is performed in an "n" by "n" ANDing gate array where "n" equals the length of the instruction buffer of the microprocessor.

 As will be appreciated by those skilled in the art,
25 various other embodiments of the cache pollution

avoidance unit according to the invention are possible relative to means of storing dependencies, means of performing logical operations, and means of storing, accessing, and decoding cache "miss" states.

5

BRIEF DESCRIPTION OF THE DRAWINGS

The accompanying drawings, which are incorporated in, and constitute a part of this specification, illustrate embodiments of the invention and, together with the description, serve to explain the principles of the invention. In the drawings:

FIG. 1 is a block diagram of a microprocessor system including an embodiment of a cache pollution avoidance unit 102 according to the present invention for avoiding cache pollution due to speculative memory operations;

FIG. 2 is a microprocessor program instruction sequence forming a portion of a microprocessor program for execution on the microprocessor system of FIG. 1;

FIG. 3 is a schematic diagram of an operation of a microprocessor pipeline in the microprocessor system of FIG. 1 on the microprocessor program instruction sequence of FIG. 2;

FIGS. 4A and 4B are process flow diagrams showing a method of using the cache pollution avoidance unit 102

of FIG. 1 with the microprocessor program instruction sequence of FIG. 2; and

FIG. 5 is a schematic diagram of one embodiment of the cache pollution avoidance unit of FIG. 1.

5

DETAILED DESCRIPTION

FIG. 1 is a block diagram of a microprocessor system 100 including an embodiment of a cache pollution avoidance unit 102 according to the present invention for avoiding cache pollution due to speculative memory operations. Microprocessor program instructions from an instruction cache (not shown) are fetched by an instruction fetch unit 104 and decoded in an instruction decode unit 106 in a manner well known to those of skill in the art. As is also known in the art, as instructions are fetched and decoded, dependency states between producer load instructions and consumer load instructions are determined as "true" or "false" in a dependency checker 108.

20 Dependency checker 108 is coupled to an instruction scheduler 112. The dependency state conditions determined by dependency checker 108 are stored in instruction scheduler 112, which further contains an "n" wide instruction buffer 111. In one embodiment, instruction scheduler 112 uses the dependency state

25

information to dispatch instructions contained in instruction buffer 111 for execution when instruction operands become available.

As described more fully below with reference to FIG. 5, according to one embodiment of the present invention, dependency checker 108 is also coupled to "n" row by "n" column dynamic memory dependency table 110 contained within cache pollution avoidance unit 102. As also described more fully below with reference to FIG. 5, in one embodiment, an ANDing gate array 103 within cache pollution avoidance unit 102 is also coupled to dynamic memory dependency table 110.

Instructions are fetched/decoded by instruction fetch unit 104 and instruction decode unit 106, and dependency checker 108 writes the various dependency state conditions among the fetched producer load instructions and consumer load instructions to dynamic memory dependency table 110.

As noted above, dependency checker 108 is coupled to instruction scheduler 112 and instruction scheduler 112, in turn, is coupled to an execution unit 114. Instruction scheduler 112 schedules the order of execution by execution unit 114 of microprocessor program instructions contained in instruction buffer 111. For clarity of presentation, execution unit 114 is

discussed generically as executing an operation
appropriate to a particular instruction. Those of skill
in the art will recognize that modern microprocessor
contain many execution units, such as floating-point
5 units and integer units, that perform microprocessor
functions appropriate to the operation being executed.

After an instruction in instruction buffer 111 is
executed by execution unit 114, a sequentially later
microprocessor instruction replaces the executed
10 instruction in instruction buffer 111. As also
described more fully below with reference to FIG. 5,
when sequentially later instructions replace executed
instructions in the instruction buffer 111, cache
pollution avoidance unit 102 updates dynamic memory
15 dependency table 110 to reflect dependencies among
producer load instructions and consumer load
instructions then in instruction buffer 111.

In one embodiment, a cache system 116 is coupled to
both execution unit 114 and cache pollution avoidance
20 unit 102. When instruction scheduler 112 schedules a
particular consumer load instruction for execution in
execution unit 114, cache pollution avoidance unit 102
receives a cache "miss" state condition returned by
cache system 116 for operand data required by the
25 particular consumer load instruction and supplied by a

particular producer load instruction on which it depends.

ANDing gate array 103 logically ANDs the cache "miss" state condition for the operand data required by the particular dependent consumer load instruction with the dependency state condition, previously stored in dynamic memory dependency table 110, between the particular consumer load instruction and the particular producer load instruction on which it depends.

10 If, for a particular consumer load instruction and a particular producer load instruction, the result of the logical ANDing of the cache "miss" state condition and the dependency state condition is true, i.e., if both the cache "miss" state condition and the dependency state condition true, access to the microprocessor memory system (not shown) and cache system 116 is denied to that particular consumer load instruction by cache pollution avoidance unit 102.

20 Illustratively, FIG. 2 is a microprocessor program instruction sequence forming a portion of a microprocessor program for execution on the microprocessor system 100 of FIG. 1. A producer load instruction "A" is a conventional microprocessor load instruction that fetches the data contained in a

microprocessor memory at a first memory location
address1 into a microprocessor first register r1.

The data contained in first register r1, after
execution of producer load instruction "A", is
5 sequentially next operated on by a calculation
instruction "B". In the example given, calculation
instruction "B" is a conventional microprocessor "add"
instruction. The operation of calculation instruction
"B" arithmetically adds to the data now in first
10 register r1, by way of execution the operation of
producer load instruction "A", to the data currently in
a microprocessor second register r2. The result of that
addition is returned to a microprocessor third register
r3.

15 The data contained in third register r3, after
execution the "add" operation of calculation instruction
"B", is sequentially next operated on by a consumer load
instruction "C". Consumer load instruction "C" is a
conventional microprocessor load instruction. Consumer
20 load instruction "C" loads the data in a microprocessor
memory at a second memory location address2 into a
microprocessor fourth register r4.

In this example however, the memory location from
which consumer instruction "C" loads data is shown as
25 second memory location address2. The accurate

determination of second memory location address2 depends directly from the results produced by the "add" operation of calculation instruction "B", which in turn depends directly from the results returned by the operation of producer load instruction "A". Thus, accurate determination of second memory location address2 depends indirectly from the results returned by the operation of producer load instruction "A", by way of the results produced by the "add" operation of calculation instruction "B".

The loading of first address location address1 into first register r1 must be completed before an accurate determination can be made for second memory location address2 contained in third register r3 at the completion of calculation instruction "B", and before the data contained in second memory location address2 may be accurately loaded into fourth register r4 by operation of first consumer load instruction "C". If first consumer load instruction "C" is allowed to execute by microprocessor system 100 before the loading of first address location address1 into first register r1 is complete, address2 data loaded into fourth register r4 may be erroneous. When cache system 116 copies erroneous second memory location address2 data in fourth register r4 , the entire data block from

erroneous second memory location address2 is written into cache memory 117 and cache pollution results.

FIG. 3 is a schematic diagram of an operation of a microprocessor pipeline 300 in microprocessor system 100 of FIG. 1 on the microprocessor program instruction sequence 200 of FIG. 2. FIGS. 4A and 4B are process flow diagrams showing a method 400 of using the cache pollution avoidance unit 102 of FIG. 1 with the microprocessor program instruction sequence 200 of FIG. 2.

Referring to FIGS. 1, 2, 3 4A and 4B together, a microprocessor pipeline 300 (FIG. 3) executes the sequence of instructions shown in FIG. 2 during a series of clock cycles 302 indicated by dashed lines. Start operation 402 (FIG. 4A) of method 400 commences the method of using cache pollution avoidance unit 102 for avoiding cache pollution due to speculative memory load operations. It is understood that prior to the commencement of method 400, microprocessor system 100 has fetched and decoded the instructions shown in FIG. 2 which are then available to instruction scheduler 112.

Start operation 402 transfers to update dynamic dependency table operation 403. When it is stated herein that a first operation transfers to a second operation, those of skill in the art understand that the

first microprocessor pipeline operation is completed and the second operation is started. In the given microprocessor instruction sequence of FIG. 2, during a first clock cycle 302A (FIG. 3), at operation 403 (FIG. 4) dependency checker 108 (FIG. 1) writes the dependency state condition between producer load instruction "A" and consumer load instruction "C", as determined by dependency checker 108 (FIG. 1), to dynamic memory dependency table 110 (FIG. 1).

10 Also during first clock cycle 302A, at a pick producer load instruction operation 404, producer load instruction "A" is checked for its register operands and dispatched, sometimes altogether called picked, by instruction scheduler 112.

15 After producer load instruction "A" is picked, during a second clock cycle 302B, operations 403 and 404 transfer to commence execution of producer load instruction 406 where the execution of load instruction "A" commences in functional unit 114 (FIG. 1). After
20 execution of producer load instruction has commenced, during a third clock cycle 302C, operation 406 transfers to complete execution of producer load instruction operation 408 where execution unit 114 generates first memory location address1 and commences loading the data
25 stored at first memory location address1 to first

register r1. After first memory location address1 is generated and the loading of register r1 with the data stored at address1 is commenced, during a fourth clock cycle 302D, operation 408 transfers to commence copying
5 of producer load instruction data to cache operation 410 where execution unit 114 directs cache system 116 to begin copying the data stored at first memory location address1 to a cache memory 117 contained within cache system 116. Also during fourth clock cycle 302D, at
10 operation 410 cache system 116 also separately commences generation and comparison of a first tag T1 (FIG. 3) with a reference tag in random access memory (not shown) of cache system 116 for cache "miss" determination.

After cache system 116 begins copying the data
15 stored at first memory location address1 to cache, during a fifth clock cycle 302E, operation 410 transfers to a pick calculation instruction 412 where calculation instruction "B" is picked by instruction scheduler 112 of microprocessor system 100. At operation 412 cache
20 system 116 continues the operation, commenced at operation 410, of copying the data at first memory address1 to cache memory 117 and continues the comparison of tag T1 with the reference tag in random access memory.

After calculation instruction "B" is picked, during a sixth clock cycle 302F, operation 412 transfers to commence execution of calculation instruction 414 (FIG. 4B) where execution unit 114 starts the summing of the data in register r1 with the data in register r2 for placement in register r3.

However, also during sixth clock cycle 302F, microprocessor system 100 speculatively commences the execution of the "add" operation of calculation instruction "B" without yet knowing whether cache system 116 has completed copying of the data contained in first register r1, as produced by producer load instruction "A" at first memory location address1, into cache memory 117.

Thus, if cache system 116 returns a cache "miss" state condition for first memory location address1 in cache memory 117 in a microprocessor clock cycle 302 that is later than sixth clock cycle 302F, calculation instruction "B" has already commenced execution using erroneous data then in first register r1 and not the desired data contained in first memory location address1 as generated by producer load instruction "A" and as copied to cache memory 117. If a cache "miss" for first memory location address1 occurs, subsequent execution of first consumer load instruction "C" at a clock cycle 302

later than sixth clock cycle 302F likewise loads erroneous operand data contained into erroneously calculated second memory location address2. Since cache system 116 contains the erroneous data stored in
5 erroneously calculated second memory location address2 to cache memory 117, for potential use by sequentially later instructions, erroneous cache data will displace proper cache data in cache memory 117.

Thus, in the prior art and absent cache pollution
10 avoidance unit 102 of the present invention, cache pollution would result. Accordingly, at operation 414 cache system 116 also separately picks consumer load instruction "C", i.e., checks the dependencies of consumer load instruction "C" with sequentially early
15 producer load instruction "A".

After calculation instruction "B" has commenced, during a seventh clock cycle 302G, operation 414 transfers to complete execution of calculation instruction and determine cache "miss" state condition
20 operation 416 where the sum of the of data in register r1 and data in register r2 is returned to register r3. However, as described above, in this example, register r3 may contained the erroneous results of the addition of the erroneous data in register r1 with the data in

register r2 at the completion of execution of
calculation instruction "B".

Accordingly, during operation 416 the cache memory
117 "miss" state condition for the data stored at
5 address1 is also determined by cache system 116. Also,
during operation 416, the determined cache "miss" state
condition for the data stored at address1, is logically
combined, in one embodiment logically ANDed, with the
dependency state condition contained in dynamic memory
10 dependency table 117 of consumer load instruction "B" on
producer load instruction "A". In one embodiment, ANDing
gate array 103 within cache pollution avoidance unit 102
performs the logical ANDing and outputs the logical
result to cache system 116 during operation 416.

15 While still within seventh clock cycle 302G,
operation 416 transfers to logical ANDing result
determination operation 418 where the "true" or "false"
logical ANDing result, described above, is determined.
If the logical ANDing determined at operation 418 is
20 "true", also while still within seventh clock period
302G, operation 418 transfers to squash memory access
operation 420 where cache pollution avoidance unit 102
directs execution unit 114 via cache system 116 to
squash memory access by consumer load instruction "C" to
25 cache memory 117. Thus squash memory operation 420

stops execution of consumer load instruction "C" and consumer load instruction "C" is prevented from accessing main memory and cache memory 117 from which consumer load instruction "C" is to fetch data stored at
5 address2, which may contain erroneous data. Further, since execution of consumer load instruction is stopped before cache system 116 copies possibly erroneous data to cache memory 117, cache pollution is avoided.

Operation 406 through operation 420 makeup a squash
10 memory loop 422. More than one iteration of squash memory loop 422 may be needed for cache system 116 to provide a "false" result for a cache memory 117 "miss" at operation 418. Stated another way, more than one iteration of squash memory loop 422 may be needed for
15 cache system 116 to provide a "hit" in cache memory 117 for the operand data in second memory location address2 that is required by consumer load instruction "C". Thus, squash memory loop 422 is repeatedly performed until a cache "hit" is returned by cache system 116 for
20 the operand data required by consumer load instruction "C" contained in second memory location address2.

Thus, at some point following operation 418, a cache "hit" is detected for memory location address1 by cache system 116. At that point the logical ANDing of
25 the dependency of consumer load instruction "C" on

producer load instruction "A" and the "miss" state condition of first memory location address1, performed by cache pollution avoidance unit 102 at operation 418 will be "false".

5 When the logical ANDing is determined at operation 418 as "false", also while still within seventh clock cycle 302G, operation 418 transfers to releases squash memory access operation 424 where squash memory access to consumer load instruction "C", if any, is released by
10 cache system 116.

 Operation 424 transfers to end operation 426 where method 400 for a ending the operation of method 400.

 At this point, cache pollution avoidance unit 102 releases the squash memory access state on consumer load
15 instruction "C". Execution unit 114 completes consumer load instruction "C", thus ending method 400 at end operation 424.

 Those of skill in the art will recognize that the sequence of operations and the operations in method 400
20 are illustrative only of one embodiment of the invention on the example instruction sequence given in FIG. 2 and are not intended to limit the invention to either the sequence of operations or the specific operations listed. For example, method 400 is repeatable for
25 additional load instructions in a microprocessor program

being repeated on the additional load instructions until the "end of program" is detected by microprocessor system 100. Further, the logical combination operations discussed above were directed to ANDing operations. However, those of skill in the art will readily recognize that with minimal modifications, other logical operations could be employed. Consequently, the specific ANDing operations discussed above were chosen for illustrative purposes only and should not be interpreted to limit the scope of the invention to this specific embodiment.

FIG. 5 is a schematic diagram of one embodiment of cache pollution avoidance unit 102 of FIG. 1. Referring to FIGS. 1 and 5 together, one embodiment of cache pollution avoidance unit 102 is presented in greater detail. Cache pollution avoidance unit 102 includes dynamic memory dependency table 110. As described briefly above, dynamic memory dependency table 110 is a "n" row by "n" column table consisting of a plurality of dependency table memory cells 502, formed as an array of conventional microprocessor system RAM cells.

Dependency table memory cells 502 are capable of storing one-bit binary values, sometimes called "flags", representing either a "true"/"false" condition of the dependency states among individual producer load

instructions and individual consumer load instructions, sometimes called dependency intersections 504, as determined by dependency checker 108.

Each row in dynamic memory dependency table 110 contains "n" binary bits ("1's" or "0's") each of which mark the dependency state condition between the two individual load instructions at the various dependency intersections 504 in each row. Each row of dynamic dependency table 110 describes the dependency state conditions of an individual load instruction at the dependency intersections 504 with all sequentially earlier load instructions currently in instruction buffer 111. Each row remains dedicated to a particular load instruction while the particular load instruction remains in instruction buffer 111.

After a load instruction in instruction buffer 111 is executed by execution unit 114, a sequentially later microprocessor load instruction is fetched/decoded and replaces the executed instruction in the microprocessor instruction buffer 111 of instruction scheduler 112. The row in dynamic memory dependency table 110 dedicated to the executed instruction is now available and is overwritten with the dependency state conditions at the dependency intersections 504 between the replacement sequentially later microprocessor load instruction and

the sequentially earlier load instructions remaining in instruction buffer 111.

In one embodiment, a binary "1" in a dependency table memory cell 502 represents a "true" dependency state condition and a binary "0" represents a "false" dependency state condition at dependency intersection 504 between a particular producer load instruction and a particular consumer load instruction.

Illustratively, with reference to FIGS. 1, 2, and 5, dependency table memory cell 502A contains a binary "1" value within dynamic dependency table 110 at a first dependency intersection 504A between producer load instruction "A" and consumer load instruction "C". Further, dependency table memory cell 502B contains a binary "0" value within dynamic dependency table 110 at a second dependency intersection 504B of independent consumer load instruction "D" (FIG. 2) on producer load instruction "A". The "0" value of dependency table memory cell 504B represents a "false" dependency state condition between producer load instruction "A" and second consumer load instruction "D". In the example of FIG. 1, data in memory location address3, from which second consumer load instruction "D" loads data, is programmatically independent of the results produced by the execution of producer load instruction "A".

Cache pollution avoidance unit 102 further includes cache miss ID decode unit 101 (FIGS. 1 and 5) coupled at a cache miss ID decode input 503 to a cache miss state condition output 501 of cache system 116. Cache miss ID
5 decode unit 101 receives at cache miss ID decode input 503 the cache "miss" state condition supplied by cache system 116 at cache miss state condition output 501 and converts the cache "miss" state condition to word line enables understood cache pollution avoidance unit 102.
10 Cache miss ID decode unit 101 outputs cache miss ID decode outputs 508.

In one embodiment, cache pollution avoidance unit 102 further includes an ANDing gate array 103 made up of a plurality of two-input/one-output AND gates 505
15 coupled to cache miss ID decode unit 101. Individual cache miss ID decode outputs 508 from cache miss ID decode unit 101 are coupled to ANDing gate first inputs 510-1 at separate AND gates 505 dedicated to each dependency intersection 504 between individual producer
20 load instructions and individual consumer load instructions.

Each dedicated AND gate 505 of ANDing gate array 103 is also coupled to dynamic memory dependency table 110. An ANDing gate second input 510-2 of each AND gate
25 505 is connected to a separate dependency table memory

cell 502 containing the "true"/"false" dependency state condition between individual producer load instructions and individual consumer load instructions. As noted above "true"/"false" dependency state conditions between
5 individual producer load instructions and individual consumer load instructions is dynamically supplied and updated by dependency checker 108 throughout program execution. The logical ANDing result of an individual ANDing gate 505 is output as ANDing gate output 507.

10 Illustratively, using the example program segment of FIG. 2 as described above, dependency table memory cell 502A, which represents the dependency state condition at dependency intersection 504A between consumer load instruction "C" and producer instruction
15 "A", contains a binary "1" value. As noted above, in this embodiment, the binary "1" value in dependency table memory cell 502A indicates that consumer load instruction "C" is dependent, indirectly through calculation instruction "B", on the data located in
20 microprocessor memory first memory location address1. Further, as also noted above, at the completion of execution of producer load instruction "A", the data located in microprocessor memory first memory location address1 is the correct data required by consumer load
25 instruction "C". Finally, as also noted above, at the

completion of execution of producer load instruction
"A", the data at first memory location address1 is
copied to cache memory 117 (FIGS. 1 and 5) for use by
instructions sequentially later than producer load
5 instruction "A". The "1" value contained in dependency
table memory cell 502A is coupled to ANDing gate second
input 510A-2 of ANDing gate 505A.

ANDing gate 505A outputs the logical ANDing result
of ANDing gate first input 510A-1 and ANDing gate second
10 input 510A-2 to cache system 116 as ANDing gate output
507A. If ANDing gate output 507A is "true", i.e., has a
binary value of "1", cache systems 116 directs execution
unit 114 to squash memory access to consumer load
instruction "C". If ANDing gate output 507A is "false",
15 i.e., has a binary value of "0", memory access to
consumer load instruction "C" is not squashed by cache
system 116.

ANDing gate output 507A is "true" so long as both
ANDing gate first input 510A-1 and ANDing gate second
20 input 510A-2 are true. In the example given, ANDing
gate first input 510A-1 is always true when both
producer load instruction "A" and consumer load
instruction "C" are in instruction buffer 111 of
microprocessor system 100 (FIG. 1). In the example
25 given, the dependency state condition between producer

load instruction "A" and consumer load instruction "C" is programmatically fixed as "true".

However, ANDing gate first input 510A-1 is true only when a cache "miss" returned by cache system 116 is true for the operand data required by consumer load instruction "C" as contained in first memory location address1 at the completion of the execution of producer load instruction "A". Thus, when cache system 116 returns a "false" cache "miss" condition, i.e., when cache miss ID decode output 508A has a binary value of "0", memory access to consumer load instruction "C" is released. At this point consumer load instruction "C" may access memory to load accurate operand data located at second memory location address2. Since cache system 116 copies only accurate operand data in second memory location address2 to cache memory 117, inaccurate cache data is not created. Thus, cache pollution avoidance unit 102 avoids the creation of cache pollution due to the speculative execution of consumer load instruction "C".

In one another embodiment, dynamic dependency table 110 is replaced with lists of unique producer load instruction IDs (not shown) for each consumer load instruction "C". When producer load instruction "B" misses in cache, a comparator (not shown), replacing

ANDing gate array 103, is used to squashed memory access
to dependent consumer load instruction "C". This
embodiment is advantageous because it requires
relatively small instruction buffers and lower frequency
5 microprocessors.

As discussed above, the present invention provides
a system, method, and microprocessor architecture for
avoiding cache pollution caused by speculative memory
load operations. While configurations and methods
10 according to the invention have been particularly shown
and described with reference to a specific embodiment,
it will be understood by those skills in the art that
various other changes in the form and details may be
made without departing from the spirit and scope of the
15 invention. For example, the logical combination
operations discussed above were directed to ANDing
operations. However, those of skill in the art will
readily recognize that with minimal modifications, other
logical operations could be employed. Also, the size
20 of the dynamic memory dependency table is not limited to
an "n" row by "n" column table where "n" is the size of
the microprocessor instruction buffer. Accordingly,
these and other variations are equivalent to the
specific implementations and embodiments described
25 herein.